

Modem

Box content: Modem, Ethernet cable, 12V charger



1

Connect the charger to the power port of the modem and to the electrical outlet



2

Connect the coaxial cable to the modem and make sure it is well clipped



3

Connect the ethernet cable first to your modem and the other end to the router in the blue port (internet)

Router

Box content: Router, Ethernet cable, AC750 9V and AC1200 12V charger



1

Connect the charger to the router's power port and to the electrical outlet



2

Connect the other end of the Ethernet cable from the modem to the blue internet port on the router.



3

Wait for the router to turn on and connect your equipment to the wifi using the information you received on the label sent to you (Name of the network: Bravo Telecom... and the password as indicated on the bottom of the router)

If you prefer to connect the equipment by cable, use the cable supplied with the router and connect it to one of the 4 orange ports from 1 to 4



Phone

Content: Cisco adapter, ethernet cable, 5V charger



1

Connect the charger to the Cisco power port and to the electrical outlet



2

Connect the Ethernet cable to the blue port on the Cisco and the other end to one of the Ethernet ports on the router which are numbered from 1 to 4



3

Connect the RJ11 cable from the phone to port 1 of the Cisco

Bravobox

Contents: Bravo box, HDMI cable, 5V charger, remote control



1

Connect the charger to the power port of the box and to the electrical outlet



2

Connect the HDMI cable to the HDMI port of the Bravo Box and to the HDMI port of the TV set



3

Connect your Bravo Box in wifi to your router with the information you have in the routers

Connect Bravo box in wifi

1. Click on settings (bottom right) on Network: You will find Wi-Fi = not connected, press ok
2. Select your network (If your router is not available in the list, click on See ALL)
3. After finishing inserting the password, click on enter (on the visual keyboard)